



晶采光電科技股份有限公司
AMPIRE CO., LTD.

SPECIFICATIONS FOR LCD MODULE

| | |
|--------------------------|----------------------------|
| CUSTOMER | |
| CUSTOMER PART NO. | |
| AMPIRE PART NO. | AM-800600K3TMQW-01H |
| APPROVED BY | |
| DATE | |

☒ Approved For Specifications

☐ Approved For Specifications & Sample

AMPIRE CO., LTD.

**2F., No.88, Sec. 1, Xintai 5th Rd., Xizhi Dist., New Taipei City221,
Taiwan (R.O.C.)**

新北市汐止區新台五路一段 88 號 2 樓(東方科學園區 D 棟)

TEL:886-2-26967269 , FAX:886-2-26967196 or 26967270

| | | |
|--------------------|-------------------|---------------------|
| APPROVED BY | CHECKED BY | ORGANIZED BY |
| | | |

RECORD OF REVISION

| Revision Date | Page | Contents | Editor |
|---------------|------|-------------|--------|
| 2011/01/19 | - | New Release | Titan |

1. INSTRUCTION

Ampire 10.4" Display Module is a color active matrix TFT-LCD that uses amorphous silicon TFT as a switching device. This model is composed of a TFT-LCD panel , a driving circuit , power supply circuit and a LED backlight system . This TFT-LCD has a high resolution SVGA (800(R.G.B) X 600) and can display up to 16.2M colors.

1-1. Features

- 10.4" (diagonal) configuration
- Input interface voltage: 3.3V
- LCD type: Transmissive , Normally White
- LVDS Interface

1-2. Applications

- Portable TV
- Car user DVD
- Industrial application

2. PHYSICAL SPECIFICATIONS

| Item | Specifications | unit |
|-------------------------|------------------------------|-------------------|
| Display resolution(dot) | 800RGB (W) x 600(H) | dots |
| Active area | 211.2 (W) x 158.4(H) | mm |
| View area | 214.8(W) x 162.7(H) | mm |
| Pixel pitch | 0.264 (W) x 0.264 (H) | mm |
| Color configuration | R.G.B -stripe | - |
| Overall dimension | 243.0(W) x 185.6(H) x 7.2(D) | mm |
| Viewing direction | 6 o'clock | - |
| Brightness | 1000 | cd/m ² |
| Contrast ratio | 500 | - |
| Display color | 262K / 16.2M | color |
| Backlight unit | LED | - |

3. ABSOLUTE MAX. RATINGS

3-1 Electrical Absolute Rating

3-1-1 TFT LCD Module

| Item | Symbol | Values | | UNIT | Note |
|-------------------------------|--------|--------|---------|------|--------|
| | | Min. | Max. | | |
| Power voltage | VDD | -0.3 | 4.0 | V | GND=0V |
| Voltage range at any terminal | - | -0.3 | VDD+0.3 | V | |

3-2 Environment Absolute Rating

| Item | Symbol | Min. | Max. | Unit | Note |
|-----------------------|--------|------|------|------|------|
| Operating Temperature | Topa | -20 | 70 | °C | |
| Storage Temperature | Tstg | -30 | 80 | °C | |

4. ELECTRICAL CHARACTERISTICS


| Item | Symbol | Min | Typ | Max | Unit | Note |
|-----------------------------------|--------|--------|-----|--------|------|------|
| Power Voltage | VDD | - | 3.3 | - | V | |
| LED Power Voltage | VCC | - | 12 | - | V | |
| High-level Input Voltage | VIH | 0.8Vcc | - | Vcc | V | |
| Low-level Input Voltage | VIL | GND | - | 0.2Vcc | V | |
| Differential Input High Threshold | VTH | - | - | 0.1 | V | |
| Differential Input Low Threshold | VTL | -0.1 | - | - | V | |

5. OPTICAL CHARACTERISTICS


| Item | | Symbol | Conditions | Min | Typ | Max | Unit | Note |
|---------------------|-------|-------------|---|-------|-------|-------|------|------|
| Contrast Ration | | CR | Viewing normal angle $\Theta x = \Theta y = 0$ | - | 500 | - | - | (2) |
| Response Time | | TR | | - | 5 | 10 | ms | |
| | | TF | | - | 15 | 20 | ms | |
| Viewing Angle | Hor. | $\Theta x+$ | Center CR>10 | - | 70 | - | deg | (3) |
| | | $\Theta x-$ | | - | 70 | - | deg | |
| | Ver. | $\Theta y+$ | | - | 50 | - | deg | |
| | | $\Theta y-$ | | - | 60 | - | deg | |
| Module Chromaticity | Red | XR | Viewing normal angle $\Theta x = \Theta y = 0$ | 0.550 | 0.600 | 0.650 | | |
| | | YR | | 0.294 | 0.344 | 0.394 | | |
| | Green | XG | | 0.304 | 0.354 | 0.404 | | |
| | | YG | | 0.529 | 0.579 | 0.629 | | |
| | Blue | XB | | 0.105 | 0.155 | 0.205 | | |
| | | YB | | 0.076 | 0.126 | 0.176 | | |
| | White | XW | | 0.240 | 0.290 | 0.340 | | |
| | | YW | | 0.268 | 0.318 | 0.368 | | |
| Brightness | | - | ILED = 480mA | - | 1000 | - | Lux | (4) |

*Note (1) These items are measured by BM-7 in the dark room (no ambient light)


*Note (2) Definition of Response Time (TR,TF) :



***Note (3) Definition of Viewing Angle**




***Note (4) The Brightness is at the center of V.A(Viewing Area).**



6. Backlight Driving Circuit

| Item | Symbol | Min | Typ | Max | Unit | Note |
|--------------------------|--------------|-----|--------|------|------|------|
| LED Voltage | VLED | - | 19.8 | - | V | |
| LED Current | ILED | - | 480 | - | mA | |
| LED life time | - | - | 50,000 | - | Hr | |
| LED DRIVER Power Current | ICC(VCC=12V) | - | 940 | 1175 | mA | |
| Dimming Voltage | - | 3 | 3.3 | 5.5 | V | |
| Dimming duty cycle | - | 5 | - | 100 | % | |

6.1 PWM Dimming Control



7. INTERFACE

CN1 : LCM PIN Definition

| Pin no | Symbol | Function |
|--------|----------|---|
| 1 | VDD | Power Supply:3.3V |
| 2 | VDD | Power Supply:3.3V |
| 3 | GND | Power Ground |
| 4 | DPS | Reverse Scan Function [H:Enable ; L:Disable] |
| 5 | RxIN0- | Transmission Data of Pixels 0 |
| 6 | RxIN0+ | Transmission Data of Pixels 0 |
| 7 | GND | Power Ground |
| 8 | RxIN1- | Transmission Data of Pixels 1 |
| 9 | RxIN1+ | Transmission Data of Pixels 1 |
| 10 | GND | Power Ground |
| 11 | RxIN2- | Transmission Data of Pixels 2 |
| 12 | RxIN2+ | Transmission Data of Pixels 2 |
| 13 | GND | Power Ground |
| 14 | RxCLKIN- | LVDS receiver signal clock |
| 15 | RxCLKIN+ | LVDS receiver signal clock |
| 16 | GND | Power Ground |
| 17 | RxIN3- | Transmission Data of Pixels 3 |
| 18 | RxIN3+ | Transmission Data of Pixels 3 |
| 19 | RSV | Reserved for internal test. Please treat it as NC |
| 20 | SEL68 | 6/8bits LVDS data input selection [H:8bits L:6bits] |

CN2 : Backlight adjustment PIN Definition

| Pin no | Symbol | Function |
|--------|---------|--|
| 1 | VCC | Power Supply:12V |
| 2 | GND | Power Ground |
| 3 | ON/OFF | Function selection:5V-Backlight ON , GND-Backlight OFF |
| 4 | Dimming | Adjust brightness |
| 5 | N/A | No Connection |


CN4 : Backlight Power Source PIN Definition

| Pin no | Symbol | Function |
|--------|--------|--------------|
| 1 | A | Power 19.8V |
| 2 | K | Power Ground |

8. Signal Characteristics

8.1 Pixel Format Image

Following figure shows the relationship between input signal and LCD pixel format.



8.2 Scanning Direction

The following figures show the image seen from the front view. The arrow indicates the direction of scan.




Fig. 1 Normal scan (Pin4, DPS = Low or NC)




Fig. 2 Reverse scan (Pin4, DPS = High)


8.3 The Input Data Format

SEL68

SEL68 = "Low" or "NC" for 6 bits LVDS Input



SEL68 = "High" for 8 bits LVDS Input



Note1: Please follow PSWG.

Note2: R/G/B data 7:MSB, R/G/B data 0:LSB

| Signal Name | Description | Remark |
|--|--|--|
| R7 R6 R5 R4 R3 R2 R1 R0 | Red Data 7 Red Data 6 Red Data 5 Red Data 4 Red Data 3 Red Data 2 Red Data 1 Red Data 0 | Red-pixel Data For 8Bits LVDS input MSB: R7 ; LSB: R0 For 6Bits LVDS input MSB: R5 ; LSB: R0 |
| G7 G6 G5 G4 G3 G2 G1 G0 | Green Data 7 Green Data 6 Green Data 5 Green Data 4 Green Data 3 Green Data 2 Green Data 1 Green Data 0 | Green-pixel Data For 8Bits LVDS input MSB: G7 ; LSB: G0 For 6Bits LVDS input MSB: G5 ; LSB: G0 |
| B7 B6 B5 B4 B3 B2 B1 B0 | Blue Data 7 Blue Data 6 Blue Data 5 Blue Data 4 Blue Data 3 Blue Data 2 Blue Data 1 Blue Data 0 | Blue-pixel Data For 8Bits LVDS input MSB: B7 ; LSB: B0 For 6Bits LVDS input MSB: B5 ; LSB: B0 |
| RxCLKIN | LVDS Data Clock | |
| DE | Data Enable Signal | When the signal is high, the pixel data shall be valid to be displayed. |

Note: Output signals from any system shall be low or Hi-Z state when VDD is off.


9. Timing Characteristics

Horizontal Timing

| Parameter | Symbol | Spec. | | | Unit |
|---------------------------|--------|-------|------|-------|------|
| | | Min. | Typ. | Max. | |
| Horizontal Display Area | thd | 800 | | | DCLK |
| DCLK frequency | Fclk | - | 40 | 50 | MHz |
| One Horizontal Line | th | 862 | 1056 | 1200- | DCLK |
| HS pulse width(Min.) | thpw | 1 | | | DCLK |
| HS pulse width (Typical.) | thpw | - | | | DCLK |
| HS pulse width (Max.) | thpw | 40 | | | DCLK |
| HS Back Porch (Blanking) | thb | 46 | 46 | 46 | DCLK |
| HS Front Porch | thfp | 16 | 210 | 354 | DCLK |

Vertical Timing

| Parameter | Symbol | Spec. | | | Unit |
|--------------------------|--------|-------|------|------|----------------|
| | | Min. | Typ. | Max. | |
| Vertical Display Area | tvd | 600 | | | T _H |
| VS period | tv | 624 | 635 | 700 | T _H |
| VS pulse width | thpw | 1 | - | 20 | T _H |
| VS Back Porch (Blanking) | tvb | 23 | 23 | 23 | T _H |
| VS Front Porch | thfp | 1 | 12 | 77 | T _H |



10. INCOMING INSPECTION STANDARD

10-1. Scope

Specifications contain

10.1 Display Quality Evaluation

10.2 Mechanics Specification

10-2. Sampling Plan

Unless there is other agreement, the sampling plan for incoming inspection shall Follow MIL-STD-105E LEVEL II.

10-2.1 Lot size: Quantity per shipment as one lot (different model as different lot).

10-2.2 Sampling type: Normal inspection, single sampling.

10-2.3 Sampling level: Level II.

10-2.4 AQL: Acceptable Quality Level

Major defect: AQL=0.65

Minor defect: AQL=1.0

10-3. Panel Inspection Condition

10-3.1 Environment:

Room Temperature: $25\pm 5^{\circ}\text{C}$.

Humidity: $65\pm 5\%$ RH.

Illumination: 300 ~ 700 Lux.

10-3.2 Inspection Distance:

35-40 cm

10-3.3 Inspection Angle:

The vision of inspector should be perpendicular to the surface of the Module.

10-3.4 Inspection time :

Perceptibility Test Time: 20 seconds max.

10-4. Display Quality


10-4.1 Function Related:

The function defects of line defect, abnormal display, and no display are considered Major defects.

10-5 Bright/Dark Dots:

| Defect Type / Specification | G0 Grade | A Grade |
|-----------------------------|----------|------------|
| Bright Dots | 0 | $N \leq 3$ |
| Dark Dots | 0 | $N \leq 4$ |
| Total Bright and Dark Dots | 0 | $N \leq 6$ |

[Note 1]




Judge defect dot and adjacent dot as following.

- (1) One pixel consists of 3 sub-pixels, including R,G, and B dot.(Sub-pixel = Dot)
- (2) The definition of dot: The size of a defective dot over 1/2 of whole dot is regarded as one defective dot.
- (3) Allow above (as A, B, C and D status) adjacent defect dots, including bright and dart adjacent dot. And they will be counted 2 defect dots in total quantity.
- (4) Defects on the Black Matrix, out of Display area, are not considered as a defect or counted.
- (5) There should be no distinct non-uniformity visible through 3% ND Filter within 2 sec inspection times.


10-6 Visual Inspection specifications:

| Defect Type | Specification | Count(N) |
|--|---|------------|
| Dot Shape (Particle 、 Scratch and Bubbles in display area) | $D \leq 0.25\text{mm}$ | Ignored |
| | $0.25\text{mm} < D \leq 0.5\text{mm}$ | $N \leq 3$ |
| | $D > 0.5\text{mm}$ | $N=0$ |
| Line Shape (Particles 、 Scratch 、 Lint and Bubbles in display area) | $W \leq 0.07\text{mm}$ | Ignored |
| | $0.07\text{mm} < W \leq 0.1\text{mm} , L \leq 5\text{mm}$ | $N \leq 3$ |
| | $W > 0.1\text{mm} , L > 5\text{mm}$ | $N=0$ |

[Note 2] W : Width[mm], L : Length[mm], N : Number, ϕ : Average Diameter



[Note 3] Bright dot is defined through 3% transmission ND Filter as following.



11. QUALITY AND RELIABILITY

| Test Item | Test Conditions | Note |
|----------------------------|---|------|
| High Temperature Operation | 70±3°C , t=240 hrs | |
| Low Temperature Operation | -20±3°C , t=240 hrs | |
| High Temperature Storage | 80±3°C , t=240 hrs | 1,2 |
| Low Temperature Storage | -30±3°C , t=240 hrs | 1,2 |
| Thermal Shock Test | -20°C ~ 25°C ~ 70°C 30 m in. 5 min. 30 min. (1 cycle) Total 5 cycle | 1,2 |
| Humidity Test | 60 °C, Humidity 90%, 240 hrs | 1,2 |
| Vibration Test (Packing) | Sweep frequency : 10 ~ 55 ~ 10 Hz/1min Amplitude : 0.75mm Test direction : X.Y.Z/3 axis Duration : 30min/each axis | 2 |
| Electro Static Discharge | ±2KV, Human Body Mode, 100pF/1500Ω | |

Note 1 : Condensation of water is not permitted on the module.

Note 2 : The module should be inspected after 1 hour storage in normal conditions
(15-35°C , 45-65%RH).

Definitions of life end point :

- Current drain should be smaller than the specific value.
- Function of the module should be maintained.
- Appearance and display quality should not have degraded noticeably.
- Contrast ratio should be greater than 50% of the initial value.

12. USE PRECAUTION

12.1 Handling precautions

- 1) The polarizing plate may break easily so be careful when handling it. Do not touch, press or rub it with a hard-material tool like tweezers.
- 2) Do not touch the polarizing plate surface with bare hands so as not to make it dirty. If the surface or other related part of the polarizing plate is dirty, soak a soft cotton cloth or chamois leather in benzine and wipe off with it. Do not use chemical liquids such as acetone, toluene and isopropyl alcohol. Failure to do so may bring chemical reaction phenomena and deteriorations.
- 3) Remove any spit or water immediately. If it is left for hours, the suffered part may deform or decolorize.
- 4) If the LCD element breaks and any LC stuff leaks, do not suck or lick it. Also if LC stuff is stuck on your skin or clothing, wash thoroughly with soap and water immediately.

12.2 Installing precautions

- 1) The PCB has many ICs that may be damaged easily by static electricity. To prevent breaking by static electricity from the human body and clothing, earth the human body properly using the high resistance and discharge static electricity during the operation. In this case, however, the resistance value should be approx. 1MΩ and the resistance should be placed near the human body rather than the ground surface. When the indoor space is dry, static electricity may occur easily so be careful. We recommend the indoor space should be kept with humidity of 60% or more. When a soldering iron or other similar tool is used for assembly, be sure to earth it.
- 2) When installing the module and ICs, do not bend or twist them. Failure to do so may crack LC element and cause circuit failure.
- 3) To protect LC element, especially polarizing plate, use a transparent protective plate (e.g., acrylic plate, glass etc) for the product case.

Do not use an adhesive like a both-side adhesive tape to make LCD surface (polarizing plate) and product case stick together. Failure to do so may cause the polarizing plate to peel off.

12.3 Storage precautions

- 1) Avoid a high temperature and humidity area. Keep the temperature between 0°C and 35°C and also the humidity under 60%.
- 2) Choose the dark spaces where the product is not exposed to direct sunlight or fluorescent light.
- 3) Store the products as they are put in the boxes provided from us or in the same conditions as we recommend.

12.4 Operating precautions

- 1) Do not boost the applied drive voltage abnormally. Failure to do so may break ICs. When applying power voltage, check the electrical features beforehand and be careful. Always turn off the power to the LC module controller before removing or inserting the LC module input connector. If the input connector is removed or inserted while the power is turned on, the LC module internal circuit may break.
- 2) The display response may be late if the operating temperature is under the normal standard, and the display may be out of order if it is above the normal standard. But this is not a failure; this will be restored if it is within the normal standard.
- 3) The LCD contrast varies depending on the visual angle, ambient temperature, power voltage etc. Obtain the optimum contrast by adjusting the LC drive voltage.
- 4) When carrying out the test, do not take the module out of the low-temperature space suddenly. Failure to do so will cause the module condensing, leading to malfunctions.
- 5) Make certain that each signal noise level is within the standard (L level: $0.2V_{dd}$ or less and H level: $0.8V_{dd}$ or more) even if the module has functioned properly. If it is beyond the standard, the module may often malfunction. In addition, always connect the module when making noise level measurements.
- 6) The CMOS ICs are incorporated in the module and the pull-up and pull-down function is not adopted for the input so avoid putting the input signal open while the power is ON.
- 7) The characteristic of the semiconductor element changes when it is exposed to light emissions, therefore ICs on the LCD may malfunction if they receive light emissions. To prevent these malfunctions, design and assemble ICs so that they are shielded from light emissions.
- 8) Crosstalk occurs because of characteristics of the LCD. In general, crosstalk occurs when the regularized display is maintained. Also, crosstalk is affected by the LC drive voltage. Design the contents of the display, considering crosstalk.

12.5 Other

- 1) Do not disassemble or take the LC module into pieces. The LC modules once disassembled or taken into pieces are not the guarantee articles.
- 2) The residual image may exist if the same display pattern is shown for hours. This residual image, however, disappears when another display pattern is shown or the drive is interrupted and left for a while. But this is not a problem on reliability.
- 3) AMIPRE will provide one year warranty for all products and three months warrantee for all repairing products.

13. OUTLINE DIMENSION

